



## NADITBNC-F

Female XLR chassis connector 110  $\Omega$  input - female BNC 75  $\Omega$  output. Interface balanced and coaxial lines.

### Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match impedances 110  $\Omega$  to 75  $\Omega$
- Match balanced to coaxial lines
- Simple to use, passive units

## Technical Information

Product	
<b>Title</b>	NADITBNC-F
<b>Connection Type</b>	Adapter
<b>Gender</b>	female

Electrical	
<b>Frequencyrange</b>	0.1 - 6 MHz
<b>Rated voltage</b>	$\leq 5$ V p-p
<b>VSWR</b>	< 1.1
<b>Return loss</b>	> 26.4 dB
<b>Insertion Loss</b>	< 0.3 dB @ 0.1 MHz to 10 MHz

Mechanical	
<b>Wire size</b>	